



TRANSMITTER



Model	Frequency	Voltage	Current	Freq. Accuracy	Rf Power	Data Rate Max	Dimension
	MHz	V	mA	KHz	mW	KBaud	mm

**BT27/28** SAW RESONATOR TRANSMITTER - OOK / GASK MODULATION

<b>BT27</b>	434	3V - 5V	12	+/- 50	12 / 25	2.4 / 38.4	36 x 9.5 x 3
<b>BT28</b>	868	3V - 5V	15	+/- 100	12 / 30	2.4 / 38.4	36 x 9.5 x 3

**BT17/18** MINIATURE SAW RESONATOR TRANSMITTER - OOK / GASK MODULATION

<b>BT17</b>	434	3V - 5V	10	+/- 50	10 / 40	2.4 / 38.4	Sil v. 18 x 14.5 Pin v. 19.5 x 11 Smt v. 17.8 x 11
<b>BT18</b>	868	3V - 5V	12	+/- 100	10 / 40	2.4 / 38.4	

**BT57/58** XTAL TRANSMITTER - OOK / GASK / FSK MODULATION - 200 KHz CHANNEL SEP.

<b>BT57</b>	434	3V - 5V	12	+/- 20	15 / 20	28.8	37 x 14.5 x 4
<b>BT58</b>	868	3V - 5V	18	+/- 20	15 / 35	28.8	37 x 14.5 x 4

**BT37/38** NBFM PLL XTAL TRANSMITTER - 50 KHz CHANNEL SEP.

<b>BT37</b>	434	3V - 5V	28	+ / - 3	20	19.2	42 x 13 x 6
<b>BT38</b>	868	3V - 5V	28	+/- 10	35	19.2	42 x 13 x 6

Ste Engineering  
 Via Maniago, 15  
 20134 Milano - Italy  
 t. +39.02.2153524  
 f. +039.02.26410928  
 www.stecom.com  
 ste@stecom.com

SERIE 2



SERIE 1



SERIE 5



SERIE 3

